

<b>Title:</b>	Cómo configurar la grabación de detección de movimiento en la tarjeta SD para la cámara IP HIKVISION	<b>Version:</b>	v1.0	<b>Date:</b>	12/13/2018	
<b>Product:</b>	Cameras				<b>Page:</b>	1 of 8

## Preparacion

---

1. SD card menor a 128GB.
2. La cámara admite almacenamiento en placa

## Cómo configurar la grabación de detección de movimiento en la tarjeta SD para la cámara IP HIKVISION

---

### 1. Instale la tarjeta SD en la cámara.



<b>Title:</b>	How to set motion detection recording in SD card for HIKVISION IP camera	<b>Version:</b>	v1.0	<b>Date:</b>	12/13/2018
<b>Product:</b>	Cameras			<b>Page:</b>	2 of 8

2. Ejecute el software SADP y luego todas las cámaras IP en la misma LAN se mostrarán en el software. Configure la dirección IP para la cámara (como 10.9.97.19).

The screenshot shows the SADP software interface. On the left, a table lists 15 online devices. Device 009 is highlighted with a red box. On the right, the 'Modify Network Parameters' panel is open for device 009. The IP Address field is set to 10.9.97.19, and the Admin Password field is filled with dots. A red arrow points from the IP address field to the Admin Password field.

ID	Device Type	Status	IPv4 Address	Port	Enhanced SDK Serv...	Software Ver...	IPv4 Gate...	HTTP
001	DS-2DP1636Z-D	Active	10.9.97.36	8001	N/A	V5.3.15build ...	10.9.97.254	80
002	iDS-2CD8426G0/F-I	Active	10.9.97.84	8000	N/A	V5.4.64build ...	10.9.97.254	80
003	DS-2TD4136-25	Active	10.9.97.88	8000	N/A	V5.5.2build 1...	10.9.97.254	80
004	DS-2CD7A85G0-IZS	Active	10.9.97.85	8000	N/A	V5.5.81build ...	10.9.97.254	80
005	DS-2TD2136-15	Active	10.9.97.28	8000	N/A	V5.5.0build 1...	10.9.97.254	80
006	DS-2CD55C5G0-IZS	Active	10.9.97.55	8000	N/A	V5.5.81build ...	10.9.97.254	80
007	NNC-8000-4KB	Active	10.9.97.44	8000	N/A	V5.5.3build 1...	10.9.97.254	80
008	CMIP75122F-SE	Active	10.9.97.23	8000	N/A	V5.4.5build 1...	10.9.97.254	80
009	DS-2CD2743G0-IZS	Active	10.9.97.19	8000	N/A	V5.5.61build ...	10.9.97.254	80
010	IPC-D640H-Z	Active	10.9.97.49	8000	N/A	V5.5.52build ...	10.9.97.254	80
011	DS-2CD7A26G0/P-...	Active	10.9.97.76	8000	N/A	V5.5.60build ...	10.9.97.254	80
012	iDS-2PT9122IX-D/S	Active	10.9.97.14	8000	N/A	V5.4.10build ...	10.9.97.254	80
013	iDS-2CD6810F/C	Active	10.9.97.68	8000	N/A	V5.4.71build ...	10.9.97.254	80
014	DS-2DF6A236X-AEL	Active	10.9.97.62	8000	N/A	V5.5.8build 1...	10.9.97.254	80
015	iDS-2V5235-F836	Active	10.9.97.83	8022	N/A	V5.5.4build 1...	10.9.97.254	80

3. Ingrese la dirección IP (10.9.97.19) en el navegador IE para iniciar sesión.

The screenshot shows a web browser window with the address bar containing 'http://10.9.97.19/doorpage/login.asp'. The page displays the Hikvision logo and a login form. The form has a text input field containing 'admin' and a password input field with dots. A red arrow points from the IP address in the browser's address bar to the login form.

<b>Title:</b>	How to set motion detection recording in SD card for HIKVISION IP camera	<b>Version:</b>	v1.0	<b>Date:</b>	12/13/2018
<b>Product:</b>	Cameras			<b>Page:</b>	3 of 8

#### 4. Vaya a Configuración> Configuración avanzada> Almacenamiento> Administración de almacenamiento y luego formatee la tarjeta SD.

**HDD Management** Net HDD

<input checked="" type="checkbox"/>	HDD No.	Capacity	Free space	Status	Type	Property	Progress
<input checked="" type="checkbox"/>	1	58.27GB	42.50GB	Normal	Local	R/W	

**Quota**

Max. Picture Capacity	14.25GB
Free Size for Picture	13.50GB
Max. Record Capacity	43.50GB
Free Size for Record	29.00GB
Percentage of Picture	5%
Percentage of Record	95%

**Save**

<b>Title:</b>	How to set motion detection recording in SD card for HIKVISION IP camera	<b>Version:</b>	v1.0	<b>Date:</b>	12/13/2018
<b>Product:</b>	Cameras			<b>Page:</b>	4 of 8

## 5. Vaya a Programación de grabación y habilite Programación de grabación.

The screenshot shows the 'Record Schedule' configuration page in the HIKVISION web interface. The 'Record Schedule' tab is selected, and the 'Enable' checkbox is checked. The 'Motion' dropdown menu is open, and a red box highlights it. A red arrow points from the 'Motion' dropdown to the 'Advanced' button. The interface displays a 24-hour schedule grid for each day of the week, with a legend on the right for recording types: Continuous, Motion, Alarm, Motion | Alarm, Motion & Alarm, and Event. A 'Save' button is visible at the bottom.

## 6. Establezca el tipo de grabación en Detección de movimiento y seleccione el programa de grabación

The screenshot shows the 'Record Schedule' configuration page in the HIKVISION web interface. The 'Record Schedule' tab is selected, and the 'Enable' checkbox is checked. The 'Motion' dropdown menu is open, and a red box highlights it. A red arrow points from the 'Motion' dropdown to the 'Advanced' button. The interface displays a 24-hour schedule grid for each day of the week, with a legend on the right for recording types: Continuous, Motion, Alarm, Motion | Alarm, Motion & Alarm, and Event. A 'Save' button is visible at the bottom.

<b>Title:</b>	How to set motion detection recording in SD card for HIKVISION IP camera	<b>Version:</b>	v1.0	<b>Date:</b>	12/13/2018
<b>Product:</b>	Cameras			<b>Page:</b>	5 of 8



## 7. Haga clic en Eventos > Detección de movimiento, actívelo y luego configure el área.

The screenshot displays the HIKVISION web interface for configuring motion detection. The top navigation bar includes 'Live View', 'Playback', 'Picture', and 'Configuration' (which is highlighted in red). Below this, the 'Motion Detection' section is active, showing options to 'Enable Motion Detection' and 'Enable Dynamic Analysis for Motion', both of which are checked. The 'Area Settings' tab is selected, showing a video feed with a red grid overlay. Below the video feed, there are controls for 'Draw Area', 'Clear All', and a 'Sensitivity' slider set to 60. A 'Save' button is located at the bottom of the configuration area. The left sidebar shows the 'Event' menu item selected, with 'Basic Event' highlighted in red. A red arrow points from the 'Event' menu to the 'Motion Detection' section in the top bar.


<b>Title:</b>	How to set motion detection recording in SD card for HIKVISION IP camera	<b>Version:</b>	v1.0	<b>Date:</b>	12/13/2018
<b>Product:</b>	Cameras			<b>Page:</b>	6 of 8

## 8. Establezca todos los días de armado y luego habilite Notificar al Centro de Vigilancia y Activar Grabación. Clic en Guardar.

Area Settings **Arming Schedule** Linkage Method

 Delete  Delete All

	0	2	4	6	8	10	12	14	16	18	20	22	24
Mon	[Blue bar]												
Tue	[Blue bar]												
Wed	[Blue bar]												
Thu	[Blue bar]												
Fri	[Blue bar]												
Sat	[Blue bar]												
Sun	[Blue bar]												

 Save

<b>Title:</b>	How to set motion detection recording in SD card for HIKVISION IP camera	<b>Version:</b>	v1.0	<b>Date:</b>	12/13/2018
<b>Product:</b>	Cameras			<b>Page:</b>	7 of 8

Enable Motion Detection

Enable Dynamic Analysis for Motion

Area Settings > Arming Schedule > **Linkage Method**

<input type="checkbox"/> Normal Linkage	<input type="checkbox"/> Trigger Alarm Output	<input checked="" type="checkbox"/> <b>Trigger Recording</b>
<input type="checkbox"/> Send Email	<input type="checkbox"/> A->1	<input checked="" type="checkbox"/> <b>A1</b>
<input checked="" type="checkbox"/> <b>Notify Surveillance Center</b>		
<input type="checkbox"/> Upload to FTP/Memory Card/...		

**Save**

## 9. Vaya a Reproducción y luego podemos buscar la grabación en la tarjeta SD.

The screenshot shows the HIKVISION playback interface. At the top, there are tabs for 'Live View', 'Playback', 'Picture', and 'Configuration'. The 'Playback' tab is active. The main area displays a video feed of a ceiling with a grid pattern. The timestamp '10-17-2018 Wed 14:10:25' is visible in the top left of the video. A search bar is located in the top right corner, with a red arrow pointing to it. Below the search bar is a calendar for October 2018, with the 17th highlighted. At the bottom, there is a timeline with a red box highlighting the time '2018-10-17 14:10:24'. A red arrow also points to this time on the timeline.

<b>Title:</b>	How to set motion detection recording in SD card for HIKVISION IP camera	<b>Version:</b>	v1.0	<b>Date:</b>	12/13/2018
<b>Product:</b>	Cameras			<b>Page:</b>	8 of 8

## First Choice for Security Professionals **HIKVISION** Technical Support