

Corte de batería de bajo voltaje

ST-BD01Q — 12/24 VDC Entrada seleccionable

El corte de batería de bajo voltaje ENFORCER evita la descarga profunda de las baterías de respaldo. El ST-BD01Q se conecta directamente a la mayoría de las fuentes de alimentación o paneles de alarma de 12 o 24 VCC para una fácil instalación plug-and-play. Un interruptor maestro de encendido/apagado conecta o desconecta fácilmente la batería y fuente de alimentación de CA desde el panel de control.

Características:

- ▶ Entrada seleccionable 12/24VDC
- Punto de corte y restauración de voltaje ajustable
- Interruptor maestro de encendido/apagado
- Indicador LED verde de alimentación de CA
- Indicador LED CC de dos colores
- Incluye cables de batería y cinta adhesiva de doble cara



ST-BD01Q

Especificaciones:

Relay contact rating		7Amp@30VDC
LED indicators	AC	Green
	DC	Red: 12VDC
		Blue: 24VDC
Connections	AC input	Terminal block
	AC output	Gray wire leads
	DC	Quick-connect terminal (battery side)
		On-board male spade terminal
Dimensions		2 ³ / ₈ " x 1 ³ / ₄ " x 7/ ₈ " (60 x 45 x 22 mm)

Voltajes de operacion

	12VDC	24VDC
DC operating voltage	10~14 VDC	22~28 VDC
AC input	12~18 VAC	24~30 VAC
Adjustable cut-off range	9~10 VDC	19.2~20.3 VDC

Aplicación de muestra:

