

## DS-PKA-WLM Teclado inalámbrico

El teclado inalámbrico de la serie DS-PKA-WLM puede conectarse a panel de control de seguridad para el control de alarma .  
Zumbador. Tecnología inalámbrica bidireccional.  
Permite realizar operaciones de armado, desarmado, limpiar alarma, etc.  
Lector de tarjeta para armar y desarmar  
Los datos inalámbricos están protegidos por el cifrado AES-128.  
Panel con touch screen para la manipulación



### Modelos disponibles

- DS-PKA-WLM-433 (White)
- DS-PKA-WLM-433 (Black)
- DS-PKA-WLM-868 (White)
- DS-PKA-WLM-868 (Black)

### Características

- 433/868 MHz dos vías de comunicación inalámbrica
- AES-128 encryption
- Operation: Armado, desarmado, limpieza alarma, etc.
- Lector de tarjeta para armar y desarmar
- Panel con touch screen para la manipulación



## Especificaciones

| Model                  |                       | DS-PKA-WLM-433  | S-PKA-WLM-868 |
|------------------------|-----------------------|---|---------------|
| RF                     | RF speed              | 10.0 kbps/4.8 bps   |               |
|                        | RF frequency          | 433 MHz/868 MHz   |               |
|                        | RF modulation         | 2GFSK   |               |
|                        | RF distance           | 800 m (open area)   |               |
|                        | RF power              | 10 dBm  |               |
| Interface & component  | TAMPER switch         | 1   |               |
|                        | RF module             | Communicates with wireless control panel  |               |
|                        | Card                  | Supports standard IC card swiping   |               |
|                        | Buzzer                | 1   |               |
|                        | Serial port           | 1, reserved   |               |
|                        | Numeric               | 10 keys: 0 to 9   |               |
|                        | Function key          | 6 function keys: fire alarm, away arming, stay arming, disarming, delete, and confirm |               |
| Application & protocol | Protocol              | HIK wireless protocol: Access to wireless control panel, two-way communication        |               |
| Electrical & battery   | Power                 | 3 VDC power input   |               |
|                        | Battery type          | 4 AA batteries  |               |
|                        | Battery life span     | 3 years   |               |
| Others                 | Operation humidity    | 10% to 90% (No condensing)  |               |
|                        | Operation temperature | -10 °C to +55 °C (-4 °F to +122 °F)   |               |
|                        | Color                 | White or black  |               |
|                        | Dimension             | φ131.5 mm (5.2"); height: 23 mm (0.9")  |               |

Distributed by

✉ [ventas@rosarioseguridad.com.ar](mailto:ventas@rosarioseguridad.com.ar)

☎️ +54 9 341 6708000

☎️ +54 9 341 6799822

📷 [rosarioseguridadok](#)

📺 Rosario Seguridad

📘 Rosario Seguridad

Grupo Instaladores

📘 <https://www.facebook.com/groups/591852618012744/>

☎️ +54 9 341 6591429

☎️ +54 9 341 4577532

**Avenida Presidente Perón 3998 - Rosario - Santa Fe - Argentina****HIKVISION®****Headquarters**

No.555 Qianmo Road, Binjiang District,  
Hangzhou 310051, China  
T +86-571-8807-5998  
[overseasbusiness@hikvision.com](mailto:overseasbusiness@hikvision.com)

**Hikvision USA**  
T +1-909-895-0400  
[sales.usa@hikvision.com](mailto:sales.usa@hikvision.com)

**Hikvision Australia**  
T +61-2-8599-4233  
[salesau@hikvision.com](mailto:salesau@hikvision.com)

**Hikvision India**  
T +91-22-28469900  
[sales@pramahikvision.com](mailto:sales@pramahikvision.com)

**Hikvision Canada**  
T +1-866-200-6690  
[sales.canada@hikvision.com](mailto:sales.canada@hikvision.com)

**Hikvision Thailand**  
T +662-275-9949  
[sales.thailand@hikvision.com](mailto:sales.thailand@hikvision.com)

**Hikvision Europe**  
T +31-23-5542770  
[sales.eu@hikvision.com](mailto:sales.eu@hikvision.com)

**Hikvision Italy**  
T +39-0438-6902  
[info.it@hikvision.com](mailto:info.it@hikvision.com)

**Hikvision Brazil**  
T +55 11 3318-0050  
[Latam.support@hikvision.com](mailto:Latam.support@hikvision.com)

**Hikvision Turkey**  
T +90 [216]521 7070- 7074  
[sales.tr@hikvision.com](mailto:sales.tr@hikvision.com)

**Hikvision Malaysia**  
T +601-7652-2413  
[sales.my@hikvision.com](mailto:sales.my@hikvision.com)

**Hikvision UK & Ireland**  
T +01628-902140  
[sales.uk@hikvision.com](mailto:sales.uk@hikvision.com)

**Hikvision South Africa**  
Tel: +27 (10) 0351172  
[sale.africa@hikvision.com](mailto:sale.africa@hikvision.com)

**Hikvision France**  
T +33(0)1-85-330-450  
[info.fr@hikvision.com](mailto:info.fr@hikvision.com)

**Hikvision Kazakhstan**  
T +7-727-9730667  
[nikia.panfilov@hikvision.ru](mailto:nikia.panfilov@hikvision.ru)

**Hikvision Vietnam**  
T +84-974270888  
[sales.vt@hikvision.com](mailto:sales.vt@hikvision.com)

**Hikvision UAE**  
T +971-4-4432090  
[salesme@hikvision.com](mailto:salesme@hikvision.com)

**Hikvision Singapore**  
T +65-6684-4718  
[sg@hikvision.com](mailto:sg@hikvision.com)

**Hikvision Spain**  
T +34-91-737-16-55  
[info.es@hikvision.com](mailto:info.es@hikvision.com)

**Hikvision Tashkent**  
T +99-87-1238-9438  
[uzb@hikvision.ru](mailto:uzb@hikvision.ru)

**Hikvision Hong Kong**  
T +852-2151-1761  
[info.hk@hikvision.com](mailto:info.hk@hikvision.com)

**Hikvision Russia**  
T +7-495-669-67-99  
[saleru@hikvision.com](mailto:saleru@hikvision.com)

**Hikvision Korea**  
T +82-(0)31-731-8817  
[sales.korea@hikvision.com](mailto:sales.korea@hikvision.com)

**Hikvision Poland**  
T +48-22-460-01-50  
[info.pl@hikvision.com](mailto:info.pl@hikvision.com)

**Hikvision Indonesia**  
T +62-21-2933759  
[Sales.Indonesia@hikvision.com](mailto:Sales.Indonesia@hikvision.com)

**Hikvision Colombia**  
[sales.colombia@hikvision.com](mailto:sales.colombia@hikvision.com)