

DS-PEA4H-10

Estacion Maestra de Alarma de Panico

La estación maestra DS-PEA4H-10 admite funciones como visualización en vivo, intercomunicador, llamada de dispositivo, etc.

Está equipada con una pantalla táctil de alta definición de 10,1 pulgadas que muestra una interfaz de diseño plano.

La estación principal se aplica a áreas de seguridad como escuelas, plazas, hospitales, centros comerciales, mercados de estaciones, parques, etc.



▪ Características clave

- pantalla táctil de 10,1 pulgadas
- Pantalla de información de alarma en tiempo real
- Admite varilla de micrófono y VGA
- Soporta supresión automática de ruido y cancelación de eco
- Fácil instalación con tecnología Power over Ethernet (PoE)

▪ Especificaciones

Software features	
Intercom	Built-in Microphone, Handset, loudspeaker
Protocol	TCP/IP, HIK-SIP, and RTSP
Hardware features	
Alarm input	4
Alarm output	4
Relay output	4, relay output
Network interface	1RJ45, 10 M/100 M/1000 M self adaptive
Serial port	2, RS-485 half-duplex interface
Video interface	VGA, HDMI
Audio interface	Built-in microphone, handset, and mic support
USB	1, USB 3.0 1, USB 2.0
PSTN	RJ11, 1 for handset
SD Card	1, Micro SDXC (≤ 128 GB)
Video	
Frame rate	PAL: 25 FPS, NTSC: 30 FPS
Electrical characteristics	
Power supply	12 VDC, PoE (IEEE 802.3 at/af)
Power Consumption	≤15 W
Display	
Display screen	10.1 inch colorful TFT LCD, 1280 × 800
User interface	Flat design
General	
Operation temperature	-10 °C to 55 °C
Operation humidity	10% to 90%
Dimension(WxHxD)	with handset: 361mm (14.2 inch) × 65mm (2.6 inch) × 197mm (7.8 inch) without handset: 291mm (11.5 inch) × 41mm (1.6 inch) × 197mm (7.8 inch)
Weight	≤2.5 kg (88.2 oz)
Audio	
Audio input	Built-in microphone, handset, and mic support
Audio output	Built-in loudspeaker, and handset
Audio compression code rate	16Kbps, 64Kbps
Device management	
Camera	CMOS, 2 MP

▪ Modelo disponible

DS-PEA4H-10

Distributed by



+54 9 341 6799822

+54 9 341 4577532



+54 9 341 6591429



rosarioseguridadok



Rosario Seguridad



Grupo Instaladores

<https://www.facebook.com/groups/591852618012744/>**www.rosarioseguridad.com.ar**

Avenida Presidente Perón 3998 - Rosario - Santa Fe - Argentina

HIKVISION®**Headquarters**

No.555 Qianmo Road, Binjiang District,
Hangzhou 310051, China
T +86-571-8807-5998
overseasbusiness@hikvision.com

Hikvision USA
T +1-909-895-0400
sales.usa@hikvision.com

Hikvision Australia
T +61-2-8599-4233
salesau@hikvision.com

Hikvision India
T +91-22-28469900
sales@pramahikvision.com

Hikvision Canada
T +1-866-200-6690
sales.canada@hikvision.com

Hikvision Thailand
T +662-275-9949
sales.thailand@hikvision.com

Hikvision Europe
T +31-23-5542770
sales.eu@hikvision.com

Hikvision Italy
T +39-0438-6902
info.it@hikvision.com

Hikvision Brazil
T +55 11 3318-0050
Latam.support@hikvision.com

Hikvision Turkey
T +90 (216)521 7070- 7074
sales.tr@hikvision.com

Hikvision Malaysia
T +601-7652-2413
sales.my@hikvision.com

Hikvision UK & Ireland
T +01628-902140
sales.uk@hikvision.com

Hikvision South Africa
Tel: +27 (10) 0351172
sale.africa@hikvision.com

Hikvision France
T +33(0)1-85-330-450
info.fr@hikvision.com

Hikvision Kazakhstan
T +7-727-9730667
nikia.panfilov@hikvision.ru

Hikvision Vietnam
T +84-974270888
sales.vt@hikvision.com

Hikvision UAE
T +971-4-4432090
salesme@hikvision.com

Hikvision Singapore
T +65-6684-4718
sg@hikvision.com

Hikvision Spain
T +34-91-737-16-55
info.es@hikvision.com

Hikvision Tashkent
T +99-87-1238-9438
uzb@hikvision.ru

Hikvision Hong Kong
T +852-2151-1761
info.hk@hikvision.com

Hikvision Russia
T +7-495-669-67-99
saleru@hikvision.com

Hikvision Korea
T +82-(0)31-731-8817
sales.korea@hikvision.com

Hikvision Poland
T +48-22-460-01-50
info.pl@hikvision.com

Hikvision Indonesia
T +62-21-2933759
Sales.Indonesia@hikvision.com

Hikvision Colombia
sales.colombia@hikvision.com